921 Corporate Way, Fremont, CA 94539, USA Tel: +1-510-490-8024,
Fax:+1-510-623-7268, Web: http://www.actisys.com, E-mail: irda-info@actisys.com

⏪⏪⏪ WARNING: READ THIS BEFORE USING PRODUCT! ⏩⏩⏩

QUICK INSTALLATION GUIDE

[ACT-IR224UN/IR424UN GENERAL SETUP PROCEDURE]

1. **WARNING: Do NOT plug Adapter into USB port, until AFTER Driver on this CD has been installed!**
2. For Windows 98/ME/2000/XP/Vista /7 & Win 8, follow below steps. For *WinCE, Mac, Android & Linux OS*, please manually browse the installation CD and find the setup packed file under folder of "Driver" to extract it and set up.
3. Make sure there is no driver named: "**PL-2303 USB-to-Serial**" or "**PL-2303 Vista Driver Installer**" in **"Add or Remove Program"** of Win2K/XP or in "**Programs and Features**" of Windows Vista/Win 7/8. If exists, please **remove it first**.
4. Insert the installation CD and it will install driver into PC automatically. If you find it not AUTORUN, especially in Vista /Win 7/8, make sure the "**AUTORUN**" option under "**Control Panel=> AUTOPLAY**" has been selected. Otherwise please browse the CD and run **Autorun.exe** manually.
5. A welcome screen for PL-2303 Driver installer will show up. Click "**Next**" to continue.
6. When this Installation completes, click "**Finish**" to close the Wizard window.
7. Now plug IR adapter into USB port. It will lead you to a "**Found New Hardware**" procedure to complete the installation.
8. For details of the procedure, please refer to Chapter of "**Installation**" in the manual.
9. **[Windows 8 Note]** :The Driver Installer v1.7.0 is Only for new IC PL2303-TA which is compatible with Windows 8 under this version. If you use old IC which is PL2303-HXA inside (**check the S/N number** from the dongle backside. If its prefix does **not begin with "TA"**, then it **is IC PL2303HXA** inside.), the **autorun** file will set Auto Update on Windows Update *for Windows only* but not for hardware driver and run Driver Installer v1.5.0 automatically for you.

© Copyright 2005-2013 ACTiSYS Corp